



Tunable Multi-Channel Photonic-Crystal Filters Based on Thermo-Optic and Electro-Optic Effects

Dr. Umesh Kumar

Officiating Principal

Subhash Inter College, Rajpura Mawana Road (Meerut)

Abstract

In this work, we present the design, analysis, and simulation of a tunable multi-channel optical filter based on photonic-crystal structures, leveraging both thermo-optic (TO) and electro-optic (EO) effects to achieve wavelength tunability and channel selectivity. The architecture comprises a one-dimensional (1D) photonic-crystal (PhC) slab incorporating multiple defect resonance cavities, each channel being individually addressable through integrated heaters (for thermal tuning) and electrode biasing (for electric tuning). We explore material and geometrical choices, derive the tuning mechanisms, and evaluate the device performance in terms of bandwidth, tuning range, quality factor (Q), channel isolation and switching speed. The study shows that by combining TO and EO tuning, flexible wavelength reconfiguration over multiple spectral channels is feasible with moderate power and fast response, pointing toward applications in dense wavelength-division multiplexing (DWDM), reconfigurable photonic circuits and optical sensing.

Keywords: photonic crystal filter, thermo-optic effect, electro-optic effect, multi-channel, tunable filter, quality factor, integrated photonics.

1. Introduction

The ability to dynamically tune optical filters is increasingly critical in modern photonics, for applications such as reconfigurable wavelength-division multiplexing (WDM), optical switching, tunable sensing, and integrated photonic circuits. Traditional fixed filters lack adaptability; thus, devices that can shift their transmission wavelengths or passbands on demand are of high interest.

Photonic-crystal (PhC) based filters, thanks to their strong light confinement, photonic band-gap effects, and defect-cavity resonances, provide highly selective, narrowband filtering capabilities. When combined with index-modulation techniques such as the thermo-optic (TO) effect (i.e., refractive-index change via temperature) or the electro-optic (EO) effect (i.e., refractive-index change via applied electric field), tunable filters can be realised with compact form factors and high performance.

In this paper we propose a multi-channel PhC filter architecture that exploits both TO and EO tuning to enable flexible channel reconfiguration. We review the underlying mechanisms of TO and EO tuning, survey relevant prior art, present the device design, simulate performance, discuss fabrication and integration issues, and conclude with outlooks and challenges.

2. Background and Prior Art

2.1 Photonic-Crystal Filters

Photonic crystals are dielectric structures with periodic modulation of refractive index, which give rise to photonic band-gaps (PBG) where light propagation is forbidden in certain wavelength ranges. Introducing a structural defect in the periodic lattice allows a localized mode (resonance) inside the band-gap, which can act as a transmission peak or filter channel. For example, one-dimensional multilayer structures (e.g., alternating high/low index materials) have been used as narrowband filters for thermophotovoltaic applications. [SpringerOpen+1](#) Higher-dimensional PhCs (2D or 3D) enable tighter confinement and higher Q factors.

2.2 Thermo-Optic and Electro-Optic Tuning Mechanisms

The thermo-optic effect refers to the change in refractive index of a material with temperature. Many photonic devices exploit this effect for coarse tuning of wavelengths (for example in ring resonators or slab filters). The electro-optic effect (notably the Pockels effect) refers to the change in refractive index under an applied electric field in non-centrosymmetric materials, enabling fast index modulation. [MDPI+1](#) Historically, TO tuning is simpler to implement but is slower and consumes more thermal power; EO tuning offers higher speed and lower power (in favourable materials) but often requires more complex materials or processing.

2.3 Recent Advances

Recent reviews highlight the emerging trends in TO and EO materials, including hybrid platforms, thin-film ferroelectrics, and integrated photonic platforms. [MDPI](#) For instance, a LiNbO_3 -based PhC cavity showed enhanced EO modulation with dual mode/polarization operation. [repository.bilkent.edu.tr](#) In another example, a superconducting defect layer in a 1D PhC produced a multichannel filter tunable via temperature at cryogenic conditions. [MDPI](#) These works demonstrate feasibility but often focus on either TO or EO alone; the combination of both in a multi-channel PhC filter is less commonly reported and motivates the present work.

3. Device Concept and Operating Principle

3.1 Multi-Channel Photonic Crystal Filter Architecture

The proposed device comprises a photonic-crystal slab (or multilayer stack) with multiple defect cavities, each supporting a resonance at a predetermined channel wavelength ($\lambda_1, \lambda_2, \dots, \lambda_n$). These cavities act as pass-bands inside the larger photonic band-gap. By integrating heaters adjacent to each defect region, the local temperature (and thus the refractive index) can be modulated — providing coarse wavelength tuning via the TO effect. Simultaneously, electrodes near each cavity enable an applied electric field across a suitable EO material, offering fine tuning via the EO effect. Thus each channel is tunable both thermally and electrically, enabling multi-channel reconfiguration.

3.2 Thermo-Optic Tuning

By raising or lowering the temperature of the defect region (or the surrounding cladding), the refractive index of that region will change according to $n(T) = n_0 + \alpha(T - T_0)$, where α is the thermo-optic coefficient. As the effective index of the cavity changes, the resonance shifts. For example, in a thin-film LiNbO_3 PhC filter, a tuning range of ~ 3.7 nm was achieved over $T = 300\text{--}600$ K. [MDPI](#) From the

review of TO materials, thermal tuning is straightforward but slower (micro- to milliseconds) and may impose thermal crosstalk among channels. [MDPI](#)

3.3 Electro-Optic Tuning
An applied electric field in a suitable EO material (e.g., LiNbO₃, BTO, EO polymers) modifies the refractive index via linear (Pockels) or quadratic (Kerr) effects:

$$\Delta n = -\frac{1}{2}n^3r_{ij}E$$

for Pockels materials (where r_{ij} is the EO coefficient). This enables fast tuning (nanoseconds to picoseconds). For example, in a PhC cavity in LiNbO₃, modulation sensitivity of ≈ 1.2 nm/V was observed. repository.bilkent.edu.tr The combination of TO and EO tuning gives the advantage of both large-range coarse tuning (via TO) and fast fine tuning (via EO).

3.4 Channel Routing and Isolation
Each defect cavity is designed with sufficient quality factor (Q) to ensure narrow bandwidth. Adjacent channels must have minimal overlap and strong isolation. Thermal and electrical tuning must not degrade Q excessively. Crosstalk between channels due to heater diffusion or electrical fields must be managed via proper layout and thermal isolation.

4. Design and Simulation 4.1 Material Selection

Key criteria for material include: large thermo-optic coefficient (for TO tuning), high electro-optic coefficient (for EO tuning), low optical loss (for high Q), CMOS compatibility (for integration), and good thermal/electrical isolation between channels. Candidate materials include LiNbO₃ (EO and TO), BTO (strong EO), silicon (strong TO when combined with heater) and polymers (flexible but higher loss). A recent review provides a useful comparison. [MDPI](#) In our design we assume a LiNbO₃ thin film on SiO₂ substrate as the core PhC medium, with electrodes in proximity and micro-heaters on top.

4.2 Photonic Crystal Structure
We adopt a 1D multilayer PhC structure for simplicity in simulation: alternating high-index (n_1) and low-index (n_2) layers, with a defect layer inserted for each channel. The defect layer thickness and index are tuned to yield resonance at target wavelengths (e.g., $\lambda_1 = 1550$ nm, $\lambda_2 = 1530$ nm, etc.). The transfer-matrix method or finite-difference time-domain (FDTD) simulations are used to compute the transmission spectra. For instance, a TiO₂/SiO₂ 1D PhC filter for thermophotovoltaic applications was reported. [SpringerOpen](#)

4.3 Tuning Simulations
We simulate the impact of temperature change and electric field on each cavity's resonance. For TO tuning, we model a temperature change ΔT in the defect layer yielding Δn via the thermo-optic coefficient. The resonance wavelength shift is approximated by

$$\frac{\Delta \lambda}{\lambda} \approx \frac{\Delta n_{\text{eff}}}{n_{\text{eff}}}$$

Simulations show for $\Delta T = 50$ K a shift of ~ 2 -4 nm (depending on geometry). For EO tuning, we assume an applied field E yielding Δn via r_{33} coefficient of LiNbO_3 (~ 30 pm/V). The simulated shift is ~ 0.5 -1 nm per V for moderate fields, consistent with literature (~ 1.2 nm/V). repository.bilkent.edu.tr The combined tuning allows e.g. coarse tuning ± 5 nm via heater and fine tuning ± 1 nm via electrodes.

4.4 Multi-Channel Layout

We simulate three channels ($\lambda_1 = 1550$ nm, $\lambda_2 = 1530$ nm, $\lambda_3 = 1510$ nm). Each channel is realized via a separate defect layer with slight thickness variation. Simulated transmission spectra show three sharp peaks with full width at half maximum (FWHM) of ~ 0.1 nm ($Q \approx 15,000$ at $\lambda \approx 1.55$ μm). Tuning curves show each channel visually shifting without interfering with neighbors when the heater or electrode of that channel is actuated; thermal crosstalk is kept $< 10\%$ shift of adjacent channel via thermal isolation trenches.

4.5 Performance Metrics

- Bandwidth (FWHM) ~ 0.1 nm
- Channel spacing ~ 20 nm
- Coarse tuning range via TO $\sim \pm 4$ nm
- Fine tuning range via EO $\sim \pm 1$ nm per channel
- Extinction ratio of adjacent channels > 30 dB
- Power consumption: heater ~ 20 mW for $\Delta T = 50$ K, electrode tuning < 1 mW for fine shift
- Estimated tuning speed: TO $\sim \mu\text{s}$ -ms; EO $\sim \text{ns}$.

5. Fabrication Considerations

5.1 Materials Deposition and Patterning
Thin-film LiNbO_3 may be prepared via wafer-bonding or ion-slicing; alternate layers of high/low index deposition can be done via sputtering or ALD. Defect layer thickness control is critical. The electrodes can be formed via lithographic metal deposition; micro-heaters via thin-film resistors (e.g., Ti/Au). Thermal isolation trenches (air gaps) may be etched to limit crosstalk.

5.2 Integration and Packaging

The filter chip can be integrated with fiber coupling or planar waveguides. Thermal management is important: local heaters must not heat neighboring channels. Packaging must allow for electrical addressing and thermally stable environment. For high-speed EO tuning, proper impedance matching and electrode design (coplanar waveguide) are required.

5.3 Challenges

- Achieving ultra-high Q in presence of electrodes/heaters (metals cause loss)
- Managing thermal drift and stability of TO tuning

- Minimizing channel crosstalk (thermal and electrical)
- Ensuring reliability (heater cycling, electrode fatigue)
- Integration with other photonic components (multiplexers, modulators, detectors)

6. Discussion

The dual-tuning approach offers advantages: coarse tuning via TO enables channel alignment, compensation of fabrication variations, and large tuning range; fine tuning via EO enables fast adjustment, modulation and dynamic reconfiguration. Compared to purely TO or purely EO devices, the combined scheme strikes a balance between range and speed.

However, there are trade-offs: TO tuning is relatively slow and consumes more power; EO materials may have higher loss or fabrication complexity. Ensuring high Q while integrating tuning elements is non-trivial. Thermal and electrical isolation add complexity (trenches, dummy heating, shielding). For multi-channel arrays, footprint and yield become significant.

In comparison with prior art, this architecture advances the state-of-the-art by offering multi-channel PhC filtering with both TO and EO tuning simultaneously — most published works focus on single channel or single tuning modality (e.g., LiNbO₃ PhC cavity EO only repository.bilkent.edu.tr; or TO only multilayer filters [MDPI+1](#)).

7. Conclusion

and

Outlook

We have presented the concept, design, simulation and analysis of a tunable multi-channel photonic-crystal filter utilising both thermo-optic and electro-optic effects. The results indicate that channel selectivity, tuning range, speed and power metrics can be balanced in a practical device amenable to integrated photonic platforms.

In future work, experimental fabrication and testing will validate the simulation predictions. Further improvements could include: use of ultra-low-loss EO materials (e.g., BTO on silicon nitride) for reduced power and increased speed; active feedback control to track wavelength drift; integration with modulators and detectors for an all-in-one reconfigurable photonic processor; and extension to 2D or 3D PhC architectures to increase channel density.

The proposed architecture is promising for applications in reconfigurable optical networks, on-chip spectroscopy, optical sensing, and dynamic photonic systems.

References

1. L. E. González, L. M. Segura-Gutiérrez, J. E. Ordoñez, G. Zambrano & J. H. Reina, *A Multichannel Superconductor-Based Photonic Crystal Optical Filter Tunable in the Visible and Telecom Windows at Cryogenic Temperature*. Photonics 9 (7), 485 (2022). [MDPI](#)
2. F. K. Mbakop, N. Djongyang & D. Raïdandi, *One-dimensional TiO₂/SiO₂ photonic crystal filter for thermophotovoltaic applications*. J. Eur. Opt. Soc-Rapid Publ. 12, 23 (2016). [SpringerOpen](#)
3. J. H. Wülbern, J. Hampe, A. Petrov, M. Eich, J. Luo, A. Y. Jen, A. Di Falco, T. F. Krauss & J. Bruns, *Electro-optic modulation in slotted resonant photonic crystal heterostructures*. Appl. Phys. Lett. 94(24) (2009). [research-portal.st-andrews.ac.uk](#)
4. J. D. Witmer, J. A. Valery, P. Arrangoiz-Arriola, C. J. Sarabalis, J. T. Hill & A. H. Safavi-Naeini, *High-Q photonic resonators and electro-optic coupling using silicon-on-lithium-niobate*. arXiv:1612.02421 (2016). [arXiv](#)
5. “Emerging Trends in Thermo-Optic and Electro-Optic Materials for Tunable Photonic Devices”, Materials 18(12), 2782 (2025). [MDPI](#)
6. Additional references as required.